KUSAM-MECO®
An ISO 9001:2015 Company

FLEX CLAMP SENSOR
MODEL- KM-CCT3K

THINK SAFETY
THINK KUSAM-MECO®

■ FEATURES:

KM-CCT3K flex clamp sensor solves problems in measuring high current conductors in tight spaces. Its Rogowski coil based current sensor provides stable, safe, and high reliable measurements up to 3000A. This unique design and lightweight feature make it a great choice for professional electricians.

- **Flex clamp can measure from 1.5A to 3000A current**
- **1m drop proof**
- **Robust terminal connection**
- **Directly displays current when connected to KM-4000/KM-4002**



Preliminary Data



● **BNC adapter**

■ SPECIFICATIONS

- **AC current (A)** : 30A/300A/3000A
- **Frequency response** : 45Hz~500Hz
- **Flex clamp size** : 45.7cm (18 inches)
- **Operating temperature** : 0℃~50℃
- **Storage temperature** : -20°C~60°C
- **Storage humidity** : ≤80%RH
- **Low battery indication** : About 3.3V
- **Category ratings** : CAT IV 600V



■ GENERAL CHARACTERISTICS

- **Power :** 1.5V battery x 3
- **Weight :** 260gms Approx.
- **Dimension (W x H x D) :** 267mm x119.4mm x34mm
- **Standard accessories :** Batteries, BNC adapter, Manual

All Specifications are subject to change without prior notice.

KUSAM-MECO®
An ISO 9001:2015 Company

Shop no.18, 1st Floor, CIDCO Shopping Complex, Plot # 9, Sector-7, Rajiv Gandhi Marg, Sanpada, Navi Mumbai - 400705. **Sales Direct : +91-9867488006, 9867675093**
Email : sales@kusam-meco.co.in **Web.:** www.kusamelectrical.com